



## 32 Channel Penta Brid 4 Megs

This 32 channel version allows you to do HDCVI/AHD/TVI/CVS/IP on each channel, with 128 Mps Incoming Bandwidth, Intelligent video System. I deal for installing in office, car dealerships, restaurants.

## Specification

<b>Operating System</b>	Operating System
<b>Interoperability</b>	ONVIF 2.42, CGI Conformant
<b>Internal HDD</b>	2 SATA Ports, up to 8TB capacity for each disk
<b>Third-party Support</b>	Dahua, Arecont Vision, AXIS, Bosch, Brickcom, Canon, CP Plus, Dynacolor, Honeywell, Panasonic, Pelco, Samsung, Sanyo, Sony, Videotec, Vivotek, and more
<b>IP Camera Input</b>	32 Channel, each channel up to 5MP
<b>Smart Phone</b>	iPhone, iPad, Android
<b>Backup Mode</b>	USB Device/Network
<b>Resolution</b>	1920x1080, 1280x1024, 1280x720, 1024x768
<b>Bit Rate</b>	1Kbps ~ 6144Kbps Per Channel
<b>Main Processor</b>	Embedded Processor
<b>Record Rate</b>	Main stream: 1080P(1~15fps) 1080N/720P/960H/D1/HD1/BCIF/CIF/QCIF (1~25/30fps) Sub stream:D1/CIF/QCIF(1~15fps)
<b>OSD</b>	Camera title, Time, Video loss, Camera lock, Motion detection, Recording
<b>Two-way Talk</b>	Reuse audio in/out, RCA
<b>Video Detection</b>	Motion Detection, MD Zones: 396 (22 x 18), Video Loss and Tampering
<b>Installation</b>	Desktop installation
<b>Max. User Access</b>	128 users
<b>Trigger Events</b>	Recording, PTZ, Tour, Video Push, Email, FTP, Snapshot, Buzzer and Screen Tips
<b>Multi-screen Display</b>	1/4/8/9/16/25/36
<b>1 Port, for PTZ Control</b>	2 USB Ports (1 USB 3.0,1 USB 2.0)
<b>Power Consumption</b>	<20W (Without HDD)
<b>USB</b>	2 USB Ports (1 USB 3.0,1 USB 2.0)
<b>Power Supply</b>	DC12V/5A
<b>Record Mode</b>	Manual, Schedule (Regular, Continuous), MD (Video detection: Motion Detection, Video Loss, Tampering), Alarm, Stop
<b>Search Mode</b>	Time /Date, Alarm, MD and Exact Search (accurate to second)
<b>Interface</b>	1 HDMI, 1 VGA, 1 TV
<b>Playback Function</b>	Play, Pause, Stop, Rewind, Fast play, Slow Play, Next File, Previous File, Next Camera, Previous Camera, Full Screen, Repeat, Shuffle, Backup Selection, Digital Zoom
<b>Record Interval</b>	1 ~ 60 min (default: 60 min), Pre-record: 1 ~ 30 sec, Post-record: 10 ~ 300 sec
<b>Playback</b>	1/4/9/16
<b>Audio In/Out</b>	1/1, RCA
<b>HDCVI Camera Input</b>	32 Channel